

SMART 1000

SMART 1000 Menu:

- | | |
|---------------------------------------|------------------------------|
| 1.Memory in use | 9.Relay 2 operation mode |
| 2.Location of registered transmitters | 10.Button for relay 2 |
| 3.Add a transmitter | 11.Change PIN |
| 4.Delete a transmitter | 12.Change master transmitter |
| 5.Block a transmitter | 13.Receiver number |
| 6.Unblock a transmitter | 14.Change receiver number |
| 7.Relay 1 operation mode | 15.Restore factory settings |
| 8.Button for relay 1 | |



Menu option 1 Memory in use:

- shows how many transmitters/remotes are stored in the receiver's memory.
- Press B to check.

Menu option 2 Location of registered transmitter:

- Press B to check.
- Pressing A will display the previous position (backwards).
- Pressing B will display the next position (forwards).
- If no positions are available, wait for SMART to come out of programming mode.

Menu option 3 Add a transmitter:

- Press B to access.
- Press any button on your transmitter/remote – the transmitter/remote will be stored in the first available space in the memory.
- Alternatively, press A to manually select the position and press B to confirm. Next press any button on your transmitter/remote.
- The transmitter/remote is then stored in your chosen position.

Menu option 4 Delete a transmitter:

- Press B to access.
- Press A to choose which transmitter/remote you wish to delete.
- By using A and B you can scroll through the numbers and press B to delete the chosen position.

Menu option 5 Block a transmitter:

- To temporarily block a transmitter/remote if access has been denied.
- For example: if a customer has not paid.
- Press B, then A to enter the position, followed by B to block.

Menu option 6 Unblock the transmitter:

- Press B to access then A to enter the position followed by B to unblock.

Menu option 7 Relay 1 operation mode:

- Press B to enter. Press A to choose. If you choose 000 Latch mode will be activated.
- Latch mode means that once the transmitter/remote is pressed the relay is activated and by pressing again the relay is deactivated.
- By choosing 999 the relay is active as long as the button is held.
- If you choose 001 to 998 the relay will be active for a specified amount of time.
- For example: 004 equals 4 seconds.

Menu option 8 Button for relay 1:

- Press B to enter.
- Press any button on your transmitter/remote to set it to be active for relay 1.

Menu option 9 Relay 2 operation mode:

- Press B to enter. Press A to choose. If you choose 000 latch ON/OFF mode will be activated.
- Latch ON/OFF mode means that once the transmitter/remote is pressed the relay is activated and by pressing again the relay is deactivated.
- By choosing 999 the relay is active as long as the button is held.
- If you choose 001 to 998 the relay will be active for a specified amount of time.
- For example: 004 equals 4 seconds.

Menu option 10 Button for relay 2:

- Press B to enter.
- Press any button on your transmitter/remote to set it to be active for relay 2.

Menu option 11 Change PIN:

- Press B to access then A to choose the new PIN and B to select.
- The receiver will display the PIN. If the PIN is correct press B to accept or A to re-enter
- followed by B to confirm.

Menu option 12 Change master transmitter:

- If your receiver is visible but out of reach you are able to program a transmitter/remote as a master and the top button of the transmitter/remote will work as button A and bottom as B of the receiver (see SMART_1000_Software.pdf - step 2).

Menu option 13 Receiver number:

- Press B to display the unique site code (receiver number).

Menu option 14 Change receiver number:

- Press B to access, then A to change number, followed by B to accept.
- If the receiver number is correct press B to accept or A to re-enter followed by B to confirm.

Menu option 15 Restore factory settings:

- Press A to confirm or B to return to the main menu.

Technical Specification:

Power Supply:	12-24V AC/DC
Current Consumption:	15mA on standby
Current Output:	24V-1A relay NO
Memory Capacity:	999
Channel Output:	2
Operation Mode:	Latch ON/OFF ALAYH (As Long As You Hold) Timed (1-998 seconds)
Size:	84x60x23mm
Weight:	75g

